

## LD40-C1

In-Ground LED Uplighter



Install sheet - Page 1

### SPECIFICATION

LED recessed luminaires are class III for Safety Extra Low Voltage **DC** supply. The product should only be used with a supplied or LightGraphix approved **350mA** or **500mA** constant current driver.

**Suitable for mounting on normally flammable surfaces.**


Lamp: **C1 LED Engine.**

This fitting is **IP67** rated - Not for permanent submersion.

Lumen Maintenance: L90B5 at 90,000hrs.

LD40- C1	
Product & LED Output Code	Power Output
LD40-C1 - 350	350mA 1.2W
LD40-C1 - 500	500mA 1.7W


**/SC**  
Spring Clips



### INSTALLATION

- Bore clearance holes to suit dimensions below.
- Wire the luminaire to a specified driver.  
NOTE: Connections in wet environments. Make IP68 connection to stop water travelling up the cables into the fittings! Refer to IP connection sheet for further details.
- The LD40 can be bonded directly into a cut-out with one of the recommended adhesives; Rotabond 2000, 3M 4200 Marine Adhesive or Simson MSR Construction Adhesive.
- When using /SC Spring Clips, squeeze the mounting springs into body with finger and thumb.
- Push in the luminaire into the cut-out hole until flush with surface.
- When installing LD40 with an OB lens fitted, rotate the fitting using a grippy pair of gloves to orientate it.

**/OB**  
Oval Beam Orientation



Wall/Lit Surface

## SEE CONSTANT CURRENT WIRING SHEET FOR IN SERIES WIRING DIAGRAM

### WIRING

Do not power up until fitting is wired correctly! Constant current LEDs must be wired in series, polarity is critical. Please refer to specified driver sheet for details on the minimum and maximum number of LEDs per circuit.

### IMPORTANT

Make sure that all cables and connections are securely connected before switching on the power. Failing to do this can lead to failure of the LEDs and/or the driver. If the LEDs do not work upon power up, turn off the power source immediately and check the polarity of the wiring. Any attempt made to open up and/or modify the luminaire will invalidate the manufacturers warranty. This is inclusive of but not limited to removal of the LightGraphix product label or removal of any parts from the main body of the product including bezels, electrical components and factory fitted fixing methods (unless otherwise stated in these instructions).

CORE COLOUR & POLARITY		
Colour of Cable	Red	Black
Materials	+	-

### MAINTENANCE

Clean with soft damp cloth.  
LED: Please contact LightGraphix.